

Digi Device Discovery Tool

Purpose

This software tool is used to detect Rotronic devices within a ethernet based network.

Supported Devices

The following device families are supported:

- HF4
- HF5
- HF6
- HF8
- HLNT
- PF4 (1st generation)
- HS5

Other Rotronic devices with a ethernet port are not supported.

Use

- Execute the DigiDeviceDiscovery.exe
- It opens window (see Figure 1 – below) and starts to search automatically.\$
- A list of found devices is shown.




Figure 1: Digi Device Discovery Tool

- Double-click on a device: A web browser opens to login (see Figure 2) (default username: rotronic / default password: wlan)



ROTRONIC LAN Configuration and Management

? Help

Login

Welcome to the Configuration and Management interface of the ROTRONIC LAN

Please specify the username and password to login to the web interface.

See the User Guide and documentation for more information on logging in or retrieving a lost password.

Username:

Password:

Copyright © 2006 ROTRONIC AG All rights reserved.
www.rotronic.ch

Figure 2: Login

- After the login, the network configuration of the device can be done as DHCP, IP-Adress, DeviceName etc. (See Figure 3 – Network configuration)



ROTRONIC LAN Configuration and Management

? Help

Home

Configuration

- Network
- Serial Ports
- GPIO
- Alarms
- System
- Remote Management
- Users

Management

- Serial Ports
- Connections

Administration

- File Management
- Backup/Restore
- Update Firmware
- Factory Default Settings
- System Information
- Reboot

Logout

Home

Getting Started

Tutorial Not sure what to do next? This Tutorial can help.

System Summary

Model:	ROTRONIC LAN
IP Address:	10.75.22.29
MAC Address:	00:40:9D:54:90:41
Description:	None
Contact:	None
Location:	None
Device ID:	00000000-00000000-00409DFF-FF2389C6

User Interface

Web Interface (Default): Enabled

Custom Interface:

Copyright © 2006 ROTRONIC AG All rights reserved.
www.rotronic.ch

Figure 3: Device Network Configuration

Remark

- If the device is not found, repeat the search.
- If the search wasn't still successful, the DHCP function might be disabled and a fix IP address is set. In this case it is necessary to find out the correct subnet manually. A device can only answer a request by the Digi Device Discovery Tool if the fix IP address is within the same subnet range as the used PC.
 - E. g. IP address device: 192.168.100.50 and PC: 192.168.100.20
-> device will be found
 - E. g. IP address device: 192.168.100.50 and PC: 10.65.20.20
-> device will not be found
- Other Rotronic devices with a ethernet port are not supported.